

KT-TR1670 Transformer

16.5VAC, 40VA with Auto-Resetting PTC Fuse

PRODUCT DESCRIPTION

KT-TR1670 is a plug-in 16.5VAC, 40VA transformer that provides reliable AC power for KT-Series indoor security and surveillance applications. It is auto-resetting PTC fuse protected and includes a power indicator LED for AC input. Grounding is provided via a third screw terminal and complies with DOE Level VI Efficiency requirements for alarm industry plug-in power supplies.

FEATURES

- 16.5VAC, 40VA (40W)
- Primary: 120VAC, 60Hz, 50W
- Class 2
- Auto-resetting PTC fuse protected
- Power indicator LED
- 3 screw terminals and grounding plug
- Efficiency Level VI compliant and UL Listed
- For indoor use only



SPECIFICATIONS

ITEM #	KT-TR1670
PRIMARY	120VAC, 60Hz, 50W
SECONDARY	16.5VAC, 40VA (40W)
FUSE	PTC
OPERATING TEMPERATURE	23°F to 86°F (-5°C to 30°C)
DIMENSIONS (L x W x H)	2.2" x 2.6" x 4.1" (56 x 66 x 104mm)
WEIGHT	1.56 lbs. (0.7kg)

